

marantz



AMP 20

AMP 20 12-Channel Power Amplifier

Reference 12-Channel 200-watt-per-channel power amplifier. Pair with AV 20 to create an elite-level home theater. Marantz HDAM, Current Feedback Amplification, and balanced line level input.

Detailed and immersive sound transforms your home theater

200 watts per channel into 8Ω / 400 watts per channel into 4Ω

12 channels powers large home theaters

Bi-amp mode drives high- and low-frequency sections of loudspeakers independently

BTL Mode (Bridge mode) combines two channels into a single 400-watt per channel into 8Ω

Perfect match for Marantz AV 20 preamplifier

Balanced XLR input is ideal for reducing input noise

Porthole with analog meter measures output

Soft side lights cast a warm glow on the front surface of the amplifier

Elegant design matches rich, warm sound



The Most Musical Sound

AMP 20

Technical Specifications

Inputs/Outputs		
Audio	Main Amplifier In	Balanced & Unbalanced: 12ch (Exclusive use by a selector switch.)
Other	Speaker Terminal	SPKT-1+
	Number of Speaker Terminals	12
	Bi-Amp Drive / BTL Drive	Yes / Yes
	Level Meter	Yes
	Chassis	Copper Plated
Multi-Room		
	RS232 Control	Yes
	IR Flasher In	Yes
	Marantz Remote Bus	Yes
	DC Trigger Input / Output	1 / 1
Specifications		
	Number of Power Amps	12
	Power Output (8 ohm, 1 kHz, 0.05% 2ch Drive) Normal / BTL	200W / 400W
	Power Output (4 ohm, 1 kHz, 0.7% 2ch Drive) Normal	400W
	Power Output (8 ohm, 1 kHz, 0.7% 5ch Drive) Normal	200W
General		
	Front Display	Level Meter
	Auto Power Off	Yes
	Metal Front Panel	Yes
	Power Consumption	400W
	Power Consumption, No-Sound	110W
	Standby Consumption	0.2W
	Maximum Dimensions (W × D × H)	17.4 × 17.4 × 7.5 in.
	Weight	39.7 lbs
	What's in the Box	Main unit, quick start guide, AC cord, Amp control cable, Remote control cable, SP terminal wrench
	UPC Code	747192143930
	Limited Warranty (United States and Canada)	5-year



Design and specifications are subject to change by Marantz without notice.

www.marantz.com

